

# NON-ENCLOSED ELECTRONIC

## Transformers

# WAC LIGHTING

Responsible Lighting®



Fixture Type:

Catalog Number:

Project:

Location:

### PRODUCT DESCRIPTION

Low Voltage electronic transformer designed to be used as a replacement part for factory installed transformers or installed in a properly listed enclosure.

### FEATURES

- 1W minimum load
- All connections must be made in an enclosure for proper installations
- Dimmable with electronic low voltage dimmers. Dimmers should always be installed on the primary side of the transformer.

### SPECIFICATIONS

**Construction:** Built-in auto reset, soft start, short and overload circuit protection features. The soft start delayed start feature extends lamp life by delaying the abrupt inrush current to the lamp.

**Output:** 12V

**Frequency:** 20khz

**Details:** In the case of a system overload or short circuit the transformer will revert to a "hold" position and then automatically reset the system when the problem is solved. System protection is designed to last several hours.

**Standards:** UL recognized component part.

### ORDER NUMBER

| Model                | Voltage | Wattage    | Min Load | L                 | W                 | H                 | Class 2 | Auto Reset |
|----------------------|---------|------------|----------|-------------------|-------------------|-------------------|---------|------------|
| <b>EN-1260-R2*</b>   | 120VAC  | 12VAC 60W  | 1W       | 2 $\frac{3}{8}$ " | 1 $\frac{3}{8}$ " | 1"                | Yes     | Yes        |
| <b>EN-1260-R-AR</b>  | 120VAC  | 12VAC 60W  | 1W       | 2 $\frac{3}{8}$ " | 1 $\frac{3}{8}$ " | 1"                | Yes     | Yes        |
| <b>EN-1275-R-AR</b>  | 120VAC  | 12VAC 75W  | 1W       | 2 $\frac{3}{8}$ " | 1 $\frac{3}{8}$ " | 1"                | No      | Yes        |
| <b>EN-12100-R-AR</b> | 120VAC  | 12VAC 100W | 1W       | 3 $\frac{1}{2}$ " | 1 $\frac{1}{2}$ " | 1 $\frac{1}{8}$ " | No      | Yes        |
| <b>EN-12150-R-AR</b> | 120VAC  | 12VAC 150W | 1W       | 3 $\frac{1}{2}$ " | 1 $\frac{1}{2}$ " | 1 $\frac{1}{8}$ " | No      | Yes        |

\*U.L. Listed Class 2 Component

### ACCESSORIES

| Model         |                            | L                 | W                 | H                 |
|---------------|----------------------------|-------------------|-------------------|-------------------|
| <b>MTB-01</b> | Multiple Terminal Block    | 3 $\frac{1}{4}$ " | 1 $\frac{3}{4}$ " | $\frac{7}{8}$ "   |
| <b>METB</b>   | Enclosure & Connection Box | 6 $\frac{5}{8}$ " | 1 $\frac{5}{8}$ " | 1 $\frac{1}{8}$ " |

wacighting.com  
Phone (800) 526.2588  
Fax (800) 526.2585

Headquarters/Eastern Distribution Center  
44 Harbor Park Drive  
Port Washington, NY 11050

Central Distribution Center  
1600 Distribution Ct  
Lithia Springs, GA 30122

Western Distribution Center  
1750 Archibald Avenue  
Ontario, CA 91760