











**Control Specifications** (continued)

 <b>Magnetic Low-Voltage (MLV) Dimmers: Slide-to-Off</b>			
	<i>Description</i>	<i>Maximum Capacity</i>	<i>Model Number</i>
	Single-pole 120 V~ 60 Hz	600 VA / 450 W	NTLV-600-XX
	Single-pole 277 V~ 60 Hz	600 VA / 450 W	NTLV-600-277-XX
	Single-pole 120 V~ 60 Hz	1000 VA / 800 W	NTLV-1000-XX
	Single-pole 277 V~ 60 Hz	1000 VA / 800 W	NTLV-1000-277-XX
	Single-pole 120 V~ 60 Hz	1500 VA / 1200 W	NTLV-1500-XX
<ul style="list-style-type: none"> <li>• Maximum capacity is permitted lamp wattage.</li> <li>• 277 V~ models require neutral wire connection.</li> </ul>			
 <b>Magnetic Low-Voltage (MLV) Dimmers: Preset</b>			
	<i>Description</i>	<i>Maximum Capacity</i>	<i>Model Number</i>
	Single-pole/3-way/4-way 120 V~ 60 Hz	600 VA / 450 W	NTLV-603P-XX
	Single-pole/3-way/4-way 120 V~ 60 Hz	1000 VA / 800 W	NTLV-1003P-XX
	Single-pole/3-way/4-way 120 V~ 60 Hz	1500 VA / 1200 W	NTLV-1503P-XX
<ul style="list-style-type: none"> <li>• For 3-way or 4-way switching, use NT-3PS-XX (3-way), NT-4PS-XX (4-way), or other mechanical switches.</li> </ul>			
 <b>Fluorescent Dimmers for Lutron 3-wire fluorescent ballasts or LED drivers: Slide-to-Off</b>			
	<i>Description</i>	<i>Maximum Capacity</i>	<i>Model Number</i>
	Single-pole 120 V~ 60 Hz	16 A	NTF-10-XX
	Single-pole 277 V~ 60 Hz	8 A	NTF-10-277-XX
<ul style="list-style-type: none"> <li>• Use with Lutron 3-wire fluorescent ballasts or LED drivers only.</li> <li>• For LED loads, please see the "Report Cards" at <a href="http://www.lutron.com/ledtool">www.lutron.com/ledtool</a> for proper loading of the dimmer.</li> <li>• No derating required.</li> <li>• To determine the number of ballasts that can be controlled by Nova T☆ fluorescent dimmer, divide the control capacity by the ballast current.</li> </ul>			
 <b>Fluorescent Dimmers for Lutron 3-wire fluorescent ballasts or LED Drivers: Preset</b>			
	<i>Description</i>	<i>Maximum Capacity</i>	<i>Model Number</i>
	Single-pole/3-way 120 V~ 60 Hz	8 A	NTF-103P-XX
	Single-pole/3-way 277 V~ 60 Hz	6 A	NTF-103P-277-XX
<ul style="list-style-type: none"> <li>• Use with Lutron 3-wire fluorescent ballasts or LED drivers only.</li> <li>• For LED loads, please see the "Report Cards" at <a href="http://www.lutron.com/ledtool">www.lutron.com/ledtool</a> for proper loading of the dimmer.</li> <li>• For 3-way or 4-way switching, use NT-3PS-XX (3-way), NT-4PS-XX (4-way), or other mechanical switches. No derating required.</li> <li>• To determine the number of ballasts that can be controlled by Nova T☆ fluorescent dimmer, divide the control capacity by the ballast current.</li> </ul>			

(continued on next page...)

<b>Job Name:</b> <input style="width: 90%; height: 20px;" type="text"/>	<b>Model Numbers:</b> <input style="width: 90%; height: 20px;" type="text"/>	
<b>Job Number:</b> <input style="width: 100px; height: 20px;" type="text"/>	<input style="width: 90%; height: 20px;" type="text"/>	<input style="width: 90%; height: 20px;" type="text"/>