

7/21/2014

2 Lamp
High Ballast Factor High Efficiency
Multi-volt
High Efficiency

| | |
|--------------|--|
| Project: | |
| Catalog#: | |
| Approved by: | |

Electronic Fluorescent Ballast

F32T8 Instant Start Parallel Lamp Operation

| Lamp Type | No. Of Lamps | Lamp Watts | Line Voltage | Ballast Factor | Input Watts | Input Current (amps) | Power Factor | THD | Ballast Efficacy Factor |
|-------------|--------------|------------|--------------|----------------|-------------|----------------------|--------------|------|-------------------------|
| F32T8* | 2 | 32 | 120 | 1.18 | 74 | 0.62 | 0.98 | <10% | 1.59 |
| | 2 | 32 | 277 | 1.18 | 73 | 0.27 | 0.98 | <10% | 1.61 |
| | 1 | 32 | 120 | 1.38 | 45 | 0.37 | 0.98 | <10% | 3.06 |
| | 1 | 32 | 277 | 1.38 | 45 | 0.17 | 0.97 | <15% | 3.06 |
| F32T8/ES/30 | 2 | 30 | 120 | 1.18 | 69 | 0.58 | 0.98 | <10% | 1.71 |
| | 2 | 30 | 277 | 1.18 | 69 | 0.25 | 0.98 | <15% | 1.71 |
| | 1 | 30 | 120 | 1.38 | 44 | 0.36 | 0.98 | <10% | 3.13 |
| | 1 | 30 | 277 | 1.38 | 44 | 0.16 | 0.97 | <15% | 3.14 |
| F32T8/ES/28 | 2 | 28 | 120 | 1.18 | 64 | 0.54 | 0.98 | <10% | 1.84 |
| | 2 | 28 | 277 | 1.18 | 63 | 0.24 | 0.98 | <15% | 1.87 |
| | 1 | 28 | 120 | 1.38 | 39 | 0.33 | 0.98 | <10% | 3.53 |
| | 1 | 28 | 277 | 1.38 | 39 | 0.15 | 0.97 | <15% | 3.64 |
| F32T8/ES/25 | 2 | 25 | 120 | 1.18 | 63 | 0.53 | 0.98 | <10% | 1.87 |
| | 2 | 25 | 277 | 1.18 | 62 | 0.23 | 0.97 | <15% | 1.90 |
| | 1 | 25 | 120 | 1.38 | 38 | 0.32 | 0.98 | <10% | 3.63 |
| | 1 | 25 | 277 | 1.38 | 38 | .015 | 0.97 | <15% | 3.63 |
| F25T8 | 2 | 25 | 120 | 1.20 | 54 | 0.45 | 0.98 | <10% | 2.20 |
| | 2 | 25 | 277 | 1.20 | 54 | 0.20 | 0.97 | <15% | 2.22 |
| | 1 | 25 | 120 | 1.40 | 33 | 0.28 | 0.98 | <10% | 4.24 |
| | 1 | 25 | 277 | 1.40 | 33 | 0.13 | 0.96 | <15% | 4.24 |
| F17T8 | 2 | 17 | 120 | 1.23 | 39 | 0.33 | 0.98 | <10% | 3.15 |
| | 2 | 17 | 277 | 1.23 | 39 | 0.15 | 0.96 | <15% | 3.15 |
| | 1 | 17 | 120 | 1.42 | 25 | 0.22 | 0.95 | <10% | 5.68 |
| | 1 | 17 | 277 | 1.42 | 25 | 0.11 | 0.95 | <15% | 5.69 |
| F40T8 | 1 | 40 | 120 | 1.35 | 54 | 0.45 | 0.98 | <10% | 2.49 |
| | 1 | 40 | 277 | 1.35 | 54 | 0.20 | 0.97 | <15% | 2.50 |
| FB32T8 | 2 | 32 | 120 | 1.18 | 74 | 0.62 | 0.98 | <10% | 1.59 |
| | 2 | 32 | 277 | 1.18 | 73 | 0.274 | 0.98 | <10% | 1.61 |
| | 1 | 32 | 120 | 1.38 | 45 | 0.37 | 0.98 | <10% | 3.06 |
| | 1 | 32 | 277 | 1.38 | 45 | 0.17 | 0.97 | <15% | 3.06 |
| FB31T8 | 2 | 31 | 120 | 1.18 | 73 | 0.58 | 0.98 | <10% | 1.61 |
| | 2 | 31 | 277 | 1.18 | 71 | 0.25 | 0.98 | <10% | 1.66 |
| | 1 | 31 | 120 | 1.38 | 44 | 0.36 | 0.98 | <10% | 3.13 |
| | 1 | 31 | 277 | 1.38 | 44 | 0.16 | 0.97 | <15% | 3.14 |
| FB28T8 | 2 | 28 | 120 | 1.18 | 65 | 0.54 | 0.98 | <10% | 1.81 |
| | 2 | 28 | 277 | 1.18 | 63 | 0.24 | 0.98 | <15% | 1.87 |
| | 1 | 28 | 120 | 1.38 | 39 | 0.33 | 0.98 | <10% | 3.54 |
| | 1 | 28 | 277 | 1.38 | 39 | 0.15 | 0.97 | <15% | 3.53 |


* Primary Lamp Design

Ballast Specifications

- Ballast shall have a five-year warranty
- Ballast shall be UL certified
- Ballast shall be sound rated Class A
- Ballast shall be Class P Type 1 Outdoor
- Ballast shall have a Lamp Current Crest Factor of <1.7
- Ballast shall withstand line transients as specified in ANSI C62.41-1991
- Ballast shall comply with the limits of FCC Part 18 Class A
- Ballast shall have a lamp operating frequency greater than 40kHz
- Ballast shall have a 0°F minimum lamp starting temperature for primary lamp
- Ballast shall be Instant Start
- Ballast shall be Parallel Lamp Operation
- Ballast shall have minimum Power Factor of 98% for primary Lamp operation
- Ballast shall operate within +/- 10% of the ballast specified line voltage at 60 Hz
- Ballast shall have a maximum case hot spot temperature of 70 Celsius

• Specifications are subject to change without notice.

Wiring Diagram



Dimensions

L: 9.5"
W: 1.3"
H: 1.0"
M: 9.0"

