

Rough Service™ and Bonus Life™ Incandescent Lamps



R20



ER30



BR30



BR40



PAR38

LAMP	WATTS	BASE	VOLTS	DESCRIPTION	BEAM SPREAD	ORDERING CODE	QTY/ CASE	AVERAGE RATED LIFE	LUMENS	C.B.C.P.*	M.O.L.**
R20	28/30	MED	120	28/30 R20 HF	FLOOD	L-789	60	5,000	205	75	3.77"
	28/30	MED	120	• 28/30 R20 HF	FLOOD	L-795	60	9,000	205	50	3.77"
	30	MED	120	• 30 R20 LF	SPOT	L-114	60	20,000	195	150	3.77"
	50	MED	120	• 50 R20 LF	SPOT	L-121	60	20,000	400	300	3.77"
ER30	50 \$	MED	120	50 ER30 LF	SPOT	L-124	30	20,000	450	600	6.10"
	75 \$	MED	120	75 ER30 LF	SPOT	L-134	30	20,000	750	800	6.10"
BR30	45/50	MED	120	• 45/50 BR 30 LF	SPOT	L-801	30	9,000	320	250	5.39"
	45/50	MED	120	• 45/50 BR 30 HF	FLOOD	L-779	30	9,000	320	150	5.39"
	65	MED	120	• 65 BR 30 HF	FLOOD	L-809	30	20,000	420	200	5.39"
	75	MED	120	• 75 BR 30 HF	FLOOD	L-132E	30	20,000	750	250	5.39"
BR40	100	MED	120	100 BR40 HF	FLOOD	L-148	24	20,000	1,150	800	6.37"
	150	MED	120	150 BR40 HF	FLOOD	L-167E	24	20,000	1,500	1,000	6.37"
PAR38	54	MED	120	• 54 PAR38 FL	FLOOD	L-914	24	9,000	850	600	5.31"
	75	MED	120	• 75 PAR38 FL	FLOOD	L-135	24	20,000	750	1,600	5.70"
	100	MED	120	• 100 PAR38 FL	FLOOD	L-153	24	20,000	1,100	2,000	5.70"
	150	MED	120	• 150 PAR38 FL	FLOOD	L-173A	24	20,000	1,450	2,300	5.70"

\$ Energy Savings, 50 and 75-watt ER lamps replace 75 and 100-watt reflector lamps, respectively, while providing the same usable light.

* Center Beam Candle Power

** Maximum Overall Length (in inches)