

**Presented By:** Candela Corporation  
**Contact Phone:** (800) 922-9226  
**Contact E-mail:** sales@candelacorp.com

**Customer Name:**  
**Project Name:**  
**Fixture Type:**





GE  
Lighting

## 10042 - 100BTT/SW/CD

### GE Edison™ BT14.5

- Edison™ halogen bulbs provide a brighter, crisper light that makes your home look its best
- That's why professionals choose Edison for exceptional results and longer bulb life.
- Showcase the beauty of your home with the highest quality of light.



### GENERAL CHARACTERISTICS

Lamp Type	Halogen - A-line
Bulb	BT14.5
Base	Medium Screw (E26)
Filament	C-8
Wattage	100
Voltage	120
Rated Life	3000 hrs
Primary Application	Standard

### PHOTOMETRIC CHARACTERISTICS

Initial Lumens	1600
Color Temperature	2900 K
Nominal Initial Lumens per Watt	16

### DIMENSIONS

Maximum Overall Length (MOL)	4.75 cm
Light Center Length (LCL)	3 cm

### PRODUCT INFORMATION

Product Code	10042
Description	100BTT/SW/CD
Standard Package	Case
Standard Package GTIN	10043168100424
Standard Package Quantity	5
Sales Unit	Unit
No Of Items Per Sales Unit	1
No Of Items Per Standard Package	5
UPC	043168100427

### CAUTIONS & WARNINGS

#### Caution

- Lamp may shatter and cause injury if broken
  - Dispose of lamp in a closed container.
  - Do not use lamp if outer glass is scratched or broken.

#### Warning

- Risk of Fire
  - In table lamp, use only with shade.
  - Keep combustible materials away from lamp.
  - Use in fixture rated for this product.
- A damaged lamp emits UV radiation which may cause eye/skin injury
  - Turn power off if glass bulb is broken, even if bulb continues to light. Remove and dispose of lamp.
- Risk of Electric Shock
  - Turn power off before inspection, installation or removal.
  - Turn power off if glass bulb is broken, even if bulb continues to light. Remove and dispose of lamp.
- Risk of Burn
  - Allow lamp to cool before handling.
- Pressurized lamp--unexpected rupture may cause injury, fire, or property damage
  - Do not exceed rated voltage.
  - Do not use lamp if outer glass is scratched or broken, even if bulb continues to light. Turn power off, remove and dispose.

\*Guaranteed to last 2 years based on 4 hours use per day at 120V.