

NON-ENCLOSED ELECTRONIC Transformer

WAC LIGHTING
Responsible Lighting®



Fixture Type:

Catalog Number:

Project:

Location:

PRODUCT DESCRIPTION

Low Voltage electronic transformer designed to be used as a replacement part for factory installed transformers or installed in a properly listed enclosure.

FEATURES

- 1W minimum load
- All connections must be made in an enclosure for proper installations
- Dimmable with electronic low voltage dimmers. Dimmers should always be installed on the primary side of the transformer.

SPECIFICATIONS

Construction: Built-in auto reset, soft start, short and overload circuit protection features. The soft start delayed start feature extends lamp life by delaying the abrupt inrush current to the lamp.

Output: 24V

Details: In the case of a system overload or short circuit the transformer will revert to a "hold" position and then automatically reset the system when the problem is solved. System protection is designed to last several hours.

Standards: UL ready components

ORDER NUMBER

Model	Voltage	Wattage	Min Load	L	W	H	Class 2	Auto Reset
EN-2460-R2*	120VAC	24VAC 60W	1W	2 1/8"	1 3/8"	1"	Yes	No
EN-24100-R2*	120VAC	24VAC 100W	1W	3 3/8"	1 3/8"	1"	Yes	No
EN-2465-277-R2-AR**	277VAC	24VAC 65W	1W	2 1/8"	1 3/8"	1"	Yes	Yes

*U.L Listed Class 2 Component

** 30W max. for halogen lamp

ACCESSORIES

Model		L	W	H
MTB-01	Multiple Terminal Block	3 1/4"	1 3/4"	7/8"
METB	Enclosure & Connection Box	6 5/8"	1 5/8"	1 1/8"

waclighting.com
Phone (800) 526.2588
Fax (800) 526.2585

Headquarters/Eastern Distribution Center
44 Harbor Park Drive
Port Washington, NY 11050

Central Distribution Center
1600 Distribution Ct
Lithia Springs, GA 30122

Western Distribution Center
1750 Archibald Avenue
Ontario, CA 91760