

**FOR 2-PIN COMPACT LAMPS****LAMPS OPERATED\***

**18 & 26 Watt Quad Tube  
2-PIN lamps with integral starter**

\*Refer to Lumen Reference Chart for list of compatible lamps

**DESCRIPTION:**


The **I-26-EM-B** from IOTA Engineering is a UL Listed fluorescent emergency ballast that allows the same fixture to be used for both normal and emergency operation. In the event of a power failure, the **I-26-EM-B** switches to the emergency mode and operates **one** of the existing lamps for **90 minutes**. The unit contains a battery, charger, and inverter circuit in a single can and is designed for installation in the wireway or enclosure. The **I-26-EM-B** can be used with most 18 & 26 Watt quad tube **2-pin** compact fluorescent lamps, with an initial output of up to **650 lumens** for one lamp.

**TECHNICAL SPECIFICATIONS**

Input Voltage.....	(Dual) 120/277V, 60Hz
Input Wattage .....	3.5 Watts
Lamps Operated.....	18 & 26 Watt quad tube 2-pin lamps with integral starter
Emergency Operation .....	90 minutes
Initial Illumination.....	650 lumens
Operating Temp .....	0° to 55° C
Battery .....	24 Hour Recharge 7-10 Year Life Expectancy
Weight .....	2.5 lbs.
Approval .....	UL and CUL Listed

**CASE DIMENSIONS**

9.5" x 2.375" x 1.5" (mounting center 9.0")

**PRODUCT ADVANTAGES**

**Designed for integral installation**

**FEATURES**

Will cold start and operate all specified lamps

Long life high temperature recyclable  
Ni-Cad battery

Galvanized steel case

Includes test switch and charge indicator  
accessory kit

For use with switched or unswitched fixtures

**5-Year Warranty.** See Warranty Page  
for details.

**DL Model suitable for use in enclosed and  
gasketed fixtures**

Meets or exceeds all National Electrical Code  
and Life Safety Code Emergency Lighting  
Requirements

International Voltage and Damp Location  
models available

I-26-EM-B

FLUORESCENT EMERGENCY BALLAST

OPTIONS

CONFIGURATION
<input checked="" type="checkbox"/> TWO-PIECE TEST SWITCH AND CHARGE INDICATOR

SPECIALTY
<input type="checkbox"/> DL - SUITABLE FOR USE IN DAMP LOCATIONS AND ENCLOSED AND GASKETED FIXTURES

VOLTAGE RATINGS
<input checked="" type="checkbox"/> 120/277V 60HZ (STANDARD)
<input type="checkbox"/> 220V 50HZ
<input type="checkbox"/> 240V 60HZ
<input type="checkbox"/> 120V 50HZ

AVERAGE LUMEN RATINGS

LAMP	1 LAMP
18W PL CF 2-pin	550
26W PL CF 2-pin	650

**REMOTE MOUNTING**

When battery packs are remote mounted, consult Customer Service for the maximum allowable distance between the battery pack and lamp(s).