



C-1



C-10



C-11



C-12



C-2



C3-EVV



C-4



C-5



C-6



C-7



C-8



C-9

Image	Order Code	Description	Other Detail	V	W	Base	Life Hr	Lumen	CP	MOL (mm)	LCL (mm)	Dia (mm)	Bulb Shape	Filament
C-1	A-6331	JF 6.6A 30W GY9.5 (EXL)	EXL	6.6 Amp	30	GY9.5	1000	380	30	44.0(1in)	25.5(1.732in)	11	T3	C-8
C-1	A-6327	JF 6.6A 45W-B GY9.5 (EXM)	EXM	6.6 Amp	45	GY9.5	1000	750	60	44.0(1in)	25.5(1.732in)	11	T3	C-8
C-10	A-6315	JF 6.6A 45W DCR P30D (6315)	6315, 6.6A	6.6 Amp	45	DC Reverse Ring P30D	1000	800 lm		2.5in	1.063in	13.5	T4	C-8
C-11	A-6319	JF 6.6A 115W DCR P30D (6319)	6319, 6.6A	6.6 Amp	115	DC Reverse Ring P30D	500	2800 lm		2.489in	1.063in	13.5	T4	C-6
C-12	A-6323	JF 6.6A 185W DCR P30D (6323)	6323, 6.6A	6.6 Amp	185	DC Reverse Ring P30D	500	4400 lm		2.362in	1.063in	13.5	T4	CC-6
C-12	A-6317	JF 6.6A 200W DCR P30D (6317)	6317, 6.6A	6.6 Amp	200	DC Reverse Ring P30D	500	4800 lm		2.362in	1.063in	13.5	T4	CC-6
C-2	A-6329	JF 6.6A 150W-B GY9.5 (EWR)	EWR	6.6 Amp	150	GY9.5	500	3600	285	65.0(1.535in)	39.0(2.56in)	13.5	T4	CC-6
C-2	A-6325	JF 6.6A 200W-B GY9.5 (EZL)	EZL	6.6 Amp	200	GY9.5	500	4800	380	65.0(1.535in)	39.0(2.56in)	13.5	T4	CC-6
C-3-EVV	A-6343	JF 6.6A 115W-B GY9.5 (EVV)	EVV	6.6 Amp	115	GY9.5	500	2500	200	65.0(1.535in)	39.0(2.56in)	13.5	T4	C-6
C-4	A-6301	JF 6.6A 30W PK30d		6.6 Amp	30	PK30d	1000	377	30	37.0(0.63in)	16.0(1.457in)	13.5	T4	C-8
C-4	A-6303	JF 6.6A 45W PK30d		6.6 Amp	45	PK30d	1000	630	50	37.0(0.63in)	16.0(1.457in)	13.5	T4	C-8
C-4	A-6303F	JF 6.6A 45W PK30d W/FEMALE ENDS		6.6 Amp	45	PK30d Female End	1000	630	50	37.0(0.63in)	16.0(1.457in)	13.5	T4	C-8
C-5	A-6305	JF 6.6A 100W PK30d		6.6 Amp	100	PK30d	1000	2200	175	43.0(0.787in)	20.0(1.693in)	13.5	T4	C-6
C-6	A-6309	JF 6.6A 150W PK30d		6.6 Amp	150	PK30d	1000	3600	285	43.0(0.787in)	20.0(1.693in)	13.5	T4	CC-6
C-6	A-6313	JF 6.6A 200W PK30d		6.6 Amp	200	PK30d	1000	4800	380	43.0(0.787in)	20.0(1.693in)	13.5	T4	CC-6
C-6	A-6313F	JF 6.6A 200W PK30d W/FEMALE ENDS		6.6 Amp	200	PK30d Female End	1000	4800	380	43.0(0.787in)	20.0(1.693in)	13.5	T4	CC-6
C-7	A-6333	JF 6.6A 45W R7s		6.6 Amp	45	R7s	1000	630	50	52.0(2.047in)		9	T21/2	C-8
C-7	A-6339AL	JF 6.6A 100W/R7s Alumimum Base		6.6 Amp	100	R7s Alumi.	1000		170	2.311in		11	T3	C-8
C-8	A-6335	JF 6.6A 100W-2 R7s		6.6 Amp	100	R7s	1000	2120	170	63.6(2.504in)		11	T3	CC-8
C-8	A-6339	JF 6.6A 100W R7s		6.6 Amp	100	R7s	1000	2120	170	63.6(2.504in)		11	T3	CC-8
C-8	A-6337	JF 6.6A 200W R7s		6.6 Amp	200	R7s	1000	4240	340	63.6(2.504in)		11	T3	CC-8
C-9	A-6341	JF 6.6A 100W Wire		6.6 Amp	100	Lead Wire	1000	2120	170	50.0(1.969in)		11	T3	CC-8
C-9	A-6347	JF 6.6A 200W Wire		6.6 Amp	200	Lead Wire	1000	4240	340	50.0(1.969in)		11	T3	CC-8