

Features & Benefits

- No rewiring needed
- Works with fluorescent electronic instant start ballast
- Long life
- High CRI
- Instant on, no delay
- Convenient and quick installation
- Utilizes existing instant start or rapid start sockets
- Compatible with controls and sensors
- Works in cold temperature applications
- Glass tube for superior optical performance
- 5 Year Warranty







* EMERGENCY BALLAST RESTRICTIONS








Specification Data

Order Code	Length	Lamp Power	Input Voltage (Depend on Ballast)	сст	Initial Lumens	CRI	Beam Angle	Lamp Efficacy	System Efficacy	Life	
L48T8/835/15G-EB	48	16	120/277V, 347V	3500K	2200	83	325	135	125	50,000	Yes
L48T8/840/15G-EB	48	16	120/277V, 347V	4000K	2200	83	325	135	125	50,000	Yes
L48T8/850/15G-EB	48	16	120/277V, 347V	5000K	2200	83	325	135	125	50,000	Yes

PRODUCT SPECIFICATIONS

Photometric Data



C195(Max)

C0


C180

C90

C270

Wiring diagram





- * Not compatible with products equipped with battery backup and/or emergency ballasts.
- * Please refer to "Ballast Compatibility List" on Related Downloads.

Specification data is based on tests performed in a controlled environment and represents relative performance. Actual performance can vary depending on operating conditions. Application and performance data subject to change without notice. All specifications are nominal unless noted otherwise.