



6 LONGHORSE 6


LH6-120-L

ELECTRONIC BALLAST SPECIFICATIONS

UL & cUL APPROVED (E186503) • PATENTED

INPUT	
VOLTAGE	120 $\pm$ 10% VAC
FREQUENCY	50/60 Hz
MAXIMUM POWER	140 WATT
MAXIMUM CURRENT	1.25 AMP
PROTECTION	
• OVER CURRENT	FUSE
• VOLTAGE TRANSIENTS	MOV (PER ANSI C82.11 - 1993)
EMI /RFI	FCC PART 18-A
OUTPUT	
OPEN CIRCUIT VOLTAGE	600V RMS MAXIMUM
BALLAST MIN. STARTING TEMP	-20°F
LAMP STARTING / TEMP	INSTANT START / SEE LAMP SPECIFICATIONS
PROTECTION	
• OPEN LAMP	YES
• SHORTED LAMP	YES

APPLICATION / MECHANICAL	
RATED	TYPE 1OR 2 OUTDOOR
BLACK / WHITE WIRES	18 INCHES
RED POWER WIRES	36 INCHES
YELLOW POWER WIRE	36 INCHES
BALLAST SIZE	H 1", W 1-3/4", L 13.3"
BALLAST WEIGHT	22.4 OZ
CASE QUANTITY	50 BALLASTS
CASE WEIGHT	70 lbs



LAMP COVERAGE

WHEN OPERATED IN ACCORDANCE WITH FULHAM'S WIRING CONFIGURATIONS.

<i>LINEAR LAMPS</i>	<i>ONE OR MORE LAMPS</i>	<i>ONE LAMP ONLY</i>
T-5	F4, F6, F8, F13, F14, F21, F28 OR F35	
T-5 HO	F24 OR F39	F54 OR F80
T-6		F42 OR F64
T-8	F13, F14, F15, F17, F18, F25, F30, F40 OR F72	F70
T-8 HO		F48, F60 OR F72
T-10	F40	
T-12	F14, F15, F20, F24, F30, F36, F40, F48, F60, F64, F72, F84 or F96 (60W)	F25, F96(75W/60W)

Fulham Co., Inc.

10/27/2008

www.Fulham.com

12705 South Van Ness Ave.

Hawthorne, CA 90250

TEL: 1.323.779.2980

FAX: 1.323.754.9060

info@fulham.com

6 LONGHORSE 6

T-12 HO		F18, F24, F30, F36, F42, F48, F60, F64, F72, F84 or F96
<i>COMPACT LAMPS</i>	<i>ONE OR MORE LAMPS</i>	<i>ONE LAMP ONLY</i>
BX	24W, 27W, 36W or 40W	28W, 39W, 50W or 55W
FQD	32W	55W
QD	13W, 18W or 26W	27W
TB	13W, 18W, 26W, 32W or 42W	
2D	16W, 21W, 28W or 38W	
CIRCLINE		22W + 32W
T-5 CIRCLINE	22W or 40W	22W + 40W

Fulham Co., Inc.

10/27/2008
www.Fulham.com

12705 South Van Ness Ave.
Hawthorne, CA 90250

TEL: 1.323.779.2980

FAX: 1.323.754.9060

info@fulham.com