

WW-QWAH-8



Description: Electromagnetic ballast for (1) lamp as indicated below:

- Line Voltage: 120 vac, + 5%, - 10%, 60Hz
- Trigger Start
- Low Power Factor

Typical Performance Data								
Lamp		Input Current (Amps)	Input Power (Watts)	Power Factor	Ballast Factor	Ballast Efficacy Factor	T.H.D. %	Crest Factor
Type	#							
F20T12	1	0.58	29	< .60	.82	2.83	< 10	< 1.7
F15T8	1	0.55	25	< .60	.89	3.50	< 10	< 1.7
F15T12	1	0.61	30	< .60	.96	3.23	< 10	< 1.7
F14T12	1	0.66	30	< .60	.86	2.87	< 10	< 1.7

Application and Performance Specification Information Subject to Change without Notification.

Performance:

- Designed in accordance with ANSI C82.1
- Compatible with PLC and IR systems
- Lag type circuit

Safety:

- No PCB's
- UL listed (Class P, Indoor and Type 1 Outdoor, HL)
- CSA Certified
- Thermally Protected

Application:

- Minimum Starting Temperature: 50° F, 10° C
- Maximum Ballast Case Temperature not to exceed 90° C
- Sound Rated: A
- Remote Mounting: 20 feet with minimum 18 AWG
(refer to TechNote # 7b for other wire sizes/lengths)

Mechanical:

- Length:
- Width:
- Height:
- Lead Length (inches, ± 1) :
 - Black
 - White, Blue
 - Red (2)
- Weight:

Overall	Mounting
6 7/16"	6"
1 7/8"	
1 1/2"	
10	
17	
12	
1.9 lbs.	

Footnotes: