Presented By: **Candela Corporation** Contact Phone: (800) 922-9226

Contact E-mail:

sales@candelacorp.com



GE Lighting

97540 - 100AR111/FL24 **GE AR111**



CAUTIONS & WARNINGS

Caution

- · Lamp may shatter and cause injury if broken
- Dispose of lamp in a closed container.
- Do not use lamp if outer glass is scratched or broken.

Warning

- Pressurized lamp--unexpected rupture may cause injury, fire, or property damage
- Do not touch glass with bare hands.
- Do not use lamp if outer glass is scratched or broken.
- Use eye protection when handling lamp.
- Risk of Burn
- Allow lamp/fixture to cool before handling.
- Turn power off before installing lamp.
- Risk of Fire
- Keep combustible materials away from lamp.

Customer Name: Project Name: Fixture Type:

GENERAL CHARACTERISTICS

Lamp Type	Halogen - AR
Bulb	AR111
Base	G53
Filament	C-8
Bulb Finish	Clear
Wattage	100
Voltage	12
Rated Life	3000 hrs
Primary Application	Indoor Floodlight

PHOTOMETRIC CHARACTERISTICS

Center Beam Candlepower (CBCP)	8000
Color Temperature	2950 K
DIMENSIONS	
Maximum Overall Length	2.6400

2.6400 in(67.1 mm)

PRODUCT INFORMATION

(MOL)

Product Code Description Standard Package Standard Package GTIN Standard Package Quantity Sales Unit No Of Items Per Sales Unit No Of Items Per Standard Package UPC

Jul 1, 2010 8:10:54 PM For additional information, visit www.gelighting.com