

For more information contact www.lighting-spot.com

Applications	Retail, office, Education, Healthcare, Warehouse, Manufacturing, Food service
Ballast Efficacy Factor - BEF	2.59
Ballast Factor	0.88
Ballast Factor Type	Standard
Ballast Type	Electronic
Brand	ProLume
CSA	N
Dimmable	N
HTS code	8504100000
Input Current (Amps)	0.50
Input Frequency (Hz)	60
Input Volts (V)	120
Lamp Connection	Parallel
Lamp Type	Linear Ballast
Lamp Wattage	20
Markets	Commercial, Industrial
Nominal Open Circuit Volts	<300
Number of Lamps	2
Primary Lamp	F20T12
Product Code	E220RS/120
Product Description	F20 T12 2 LAMP ELEC 120V RS
Product Number	50110
Specification Sheet	
Start Type	Rapid Start
Warranty (Yrs)	5
Wattage (W)	34