Rev. E

Feature

- Ultra High Efficiency (Up to 94%)
- Full Power at Wide Output Current Range (Constant Power)
- 0-5V/0-10V/PWM/Timer Dimmable
- Input Surge Protection: 6 kV line-line, 10 kV line-earth
- All-Around Protection: OVP, SCP, OTP
- Waterproof (IP67) and UL Dry / Damp / Wet Location
- SELV Output
- TYPE HL, for use in a Class I, Division 2 hazardous (Classified) location
- UL Type TL (Temperature Limited)
- 7 Years Warranty





Description

The *EUG-240SxxxDT* series is a 240W, constant-current, programmable LED driver that operates from 90-305 Vac input with excellent power factor. It is created for many lighting applications including high bay, high mast, and roadway lights. The high efficiency of these drivers and compact metal case enables them to run cooler, significantly improving reliability and extending product life. To ensure trouble-free operation, protection is provided against input surge, output over voltage, short circuit, and over temperature.

Models


Adjustable Output	Full-Power Current	Default Output	Input Voltage	Output Voltage	Max.	Typical Efficiency		Factor	Model Number
Current Range	Range (1)	Current	Range(2)	•	Power			220Vac	(4)
70-1050mA	700-1050mA	700 mA	90~305 Vac/ 127~300 Vdc	114~343Vdc	240W	94.0%	0.99	0.96	EUG-240S105DT
140-2100mA	1400-2100mA	1400 mA	90~305 Vac/ 127~300 Vdc	57~171Vdc	240W	93.0%	0.99	0.96	EUG-240S210DT
280-4200mA	2800-4200mA	4200 mA	90~305 Vac/ 127~300 Vdc	29 ~ 86Vdc	240W	93.0%	0.99	0.96	EUG-240S420DT ⁽⁵⁾
445-6700mA	4450-6700mA	6700 mA	90~305 Vac/ 127~300 Vdc	18 ~ 54Vdc	240W	93.0%	0.99	0.96	EUG-240S670DT ⁽⁵⁾


Notes: (1) Output current range with constant power at 240W

- (2) Certified voltage range: UL, FCC 100-277Vac or 127-300Vdc; otherwise 100-240Vac or 127-250Vdc (except KS)
- (3) Measured at full load and 220Vac input (see below "General Specifications" for details).
- (4) All the models are certificated to KS, except EUG-240S105DT
- (5) SELV Output.

INVENTRONICS

I-V Operating Area





EUG-240S420DT 96 (1960,86) (2800,86) 80 oset,240/loset) Output Voltage(V) (4200,57)48 (4200.40)32 (4200,29) (420,29)(loset,29) 16 Programmed Operating Area Good Performance Area Allowed Operating Area 0

2400

Output Current (mA)

Note: 2800mA≤loset≤4200mA

3200

4000

4800

EUG-240S670DT 60 (3115,54) (4450,54) (445,54) 50 (loset,240/loset) 3e L 100% (10%loset 240/loset) Output Voltage(V) 40 (6700,36)30 (6700,25)20 (6700, 18)(670, 18)10 Programmed Operating Area Good Performance Area 0 3750 5000 7500 1250 2500 6250 Output Current (mA) Note: 4450mA≤loset≤6700mA

Input Specifications

Parameter	Min.	Тур.	Max.	Notes	
Input Voltage	90 Vac	-	305 Vac	127~300 Vdc	
Input Frequency	47 Hz	-	63 Hz		
Leakage Current			0.75 MIU	UL8750; 277Vac/ 60Hz, grounding effectively	
Leakage Current	-	-	0.70 mA	IEC60598-1; 240Vac/ 60Hz, grounding effectively	
Input AC Current	-	-	3.10 A	Measured at full load and 100 Vac input.	
Input AC Current	-	-	1.40 A	Measured at full load and 220 Vac input.	
Inrush Current(I ² t)	-	-	3.75 A ² s	At 220Vac input, 25°C cold start, duration=1.26 ms, 10%lpk-10%lpk. See Inrush Current Waveform for the details.	

2/15

Fax: 86-571-86601139

Rev. E

Input Specifications (Continued)

Parameter		Min.	Тур.	Max.	Notes
PF		0.9	-	-	At 100-277Vac, 50-60Hz, 70%-100% Load
THD		-	-	20%	(168-240W)
THD		-	-	10%	At 220-240Vac, 50-60Hz, 75%-100% Load (180-240W)

Output Specifications

Parameter	Min.	Тур.	Max.	Notes
Output Current Tolerance	-5%loset	-	5%loset	At full load condition
Output Current Setting(Ioset)				
Range	70 4		4050 4	
EUG-240S105DT	70 mA 140 mA	-	1050 mA 2100 mA	
EUG-240S210DT EUG-240S420DT	280 mA	-	4200 mA	
EUG-240S420DT EUG-240S670DT	445 mA	-	6700 mA	
Output Current Setting Range	445 IIIA	-	6700 IIIA	
with Constant Power				
EUG-240S105DT	700 mA		1050 mA	
EUG-240S210DT	1400 mA	_	2100 mA	
EUG-240S420DT	2800 mA	_	4200 mA	
EUG-240S670DT	4450 mA	_	6700 mA	
	11 30 IIIA	_	0700111A	
Total Output Current Ripple	-	5%lomax	10%lomax	At full load condition. 20 MHz BW
(pk-pk)				
Output Current Ripple at	_	2%lomax	_	At full load condition. Only this component
< 200 Hz (pk-pk)				of ripple is associated with visible flicker.
Startup Overshoot Current	=	-	10%lomax	At full load condition
No Load Output Voltage				
EUG-240S105DT	-	-	356 V	
EUG-240S210DT	-	-	187 V	
EUG-240S420DT	-	-	96 V	
EUG-240S670DT	=	-	60 V	
Line Regulation	-	-	±0.5%	Measured at full load
Load Regulation	_	_	±1.5%	
				1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1
Turn-on Delay Time	-	-	1.0 s	Measured at 120Vac input, 70%-100% Load
Tuni-on Delay Tillie	-	-	0.5 s	Measured at 220Vac input, 70%-100% Load
Temperature Coefficient of loset	-	0.03%/°C	-	Case temperature = 0°C ~Tc max
12V Auxiliary Output Voltage	10.8 V	12 V	13.2 V	
12V Auxiliary Output Source Current	0 mA	-	20 mA	Return terminal is "Dim-"

Note: All specifications are typical at 25°C unless otherwise stated.

Rev. E

General Specifications

General Specifications	ieneral Specifications							
Parameter	Min.	Тур.	Max.	Notes				
Efficiency at 120 Vac input:								
EUG-240S105DT	00.00/	00.00/						
lo= 700 mA lo=1050 mA	90.0% 88.5%	92.0% 90.5%	-					
EUG-240S210DT	00.570	90.576	_					
lo=1400 mA	88.5%	90.5%	_	Measured at full load and steady-state				
lo=2100 mA	88.0%	90.0%	-	temperature in 25°C ambient;				
EUG-240S420DT				(Efficiency will be about 2.0% lower if measured immediately after startup.)				
lo=2800 mA	89.0%	91.0%	-	measured inimediately after startup.)				
Io=4200 mA	87.0%	89.0%	-					
EUG-240S670DT lo=4450 mA	88.5%	90.5%	_					
Io=6700 mA	87.0%	89.0%	_					
	07.070	00.070						
Efficiency at 220 Vac input:								
EUG-240S105DT lo= 700 mA	92.0%	94.0%	_					
Io=1050 mA	90.5%	92.5%	_					
EUG-240S210DT	00.070	02.070		Management of full land and standy state				
Io=1400 mA	91.0%	93.0%	-	Measured at full load and steady-state				
lo=2100 mA	89.5%	91.5%	-	temperature in 25°C ambient; (Efficiency will be about 2.0% lower if				
EUG-240S420DT				measured immediately after startup.)				
lo=2800 mA	91.0%	93.0%	-	measured inimediately after startup.)				
lo=4200 mA EUG-240S670DT	89.5%	91.5%	-					
lo=4450 mA	91.0%	93.0%	_					
Io=6700 mA	89.5%	91.5%	_					
Efficiency at 277 Vac input: EUG-240S105DT								
lo= 700 mA	92.5%	94.5%	_					
Io=1050 mA	91.0%	93.0%	_					
EUG-240S210DT				Measured at full load and steady-state				
Io=1400 mA	92.0%	94.0%	-	temperature in 25°C ambient;				
lo=2100 mA	89.5%	91.5%	-	(Efficiency will be about 2.0% lower if				
EUG-240S420DT	91.5%	02.50/		measured immediately after startup.)				
lo=2800 mA lo=4200 mA	91.5%	93.5% 92.0%	_					
EUG-240S670DT	90.070	92.070	_					
lo=4450 mA	91.5%	93.5%	_					
lo=6700 mA	89.5%	91.5%	-					
		0.4.0.000		Measured at 220Vac input, 80%Load and				
MTBF	-	218,000	-	25°C ambient temperature (MIL-HDBK-				
		Hours		217F)				
		109,000		Measured at 220Vac input, 80%Load and				
Lifetime	-	Hours	-	70°C case temperature; See lifetime vs. Tc				
		. 10010		curve for the details				
Operating Case Temperature for Safety Tc_s	-40°C	-	+88°C					
Operating Case Temperature	-40°C	-	+75°C	Case temperature for 7 years warranty. Please see Inventronics Warranty				
for Warranty Tc_w				Statement for complete details.				
Operating Case Temperature for Type TL Tc_TL	-40°C	-	+88°C					
Storage Temperature	-40°C	-	+85°C	Humidity: 5%RH to 100%RH				
			•					

4/15

Fax: 86-571-86601139



Rev. E

General Specifications (Continued)

Parameter	Min.	Тур.	Max.	Notes
Dimensions Inches (L × W × H) Millimeters (L × W × H)	_	.35 × 2.66 × 1.5 12 × 67.5 × 39.		With mounting ear 9.17 × 2.66 × 1.56 233 × 67.5 × 39.7
Net Weight	-	1200 g	-	

Note: All specifications are typical at 25°C unless otherwise stated.

Dimming Specifications

Parameter		Min.	Тур.	Max.	Notes
Absolute Maximum Voltage on the Vdim (+) Pin		-20 V	-	20 V	
Source Cu (+)Pin	rrent on Vdim	200 uA	300 uA	450 uA	Vdim(+) = 0 V
Dimming Output	EUG-240S105DT EUG-240S210DT EUG-240S420DT EUG-240S670DT	10%loset	-	loset	700 mA ≤ loset ≤ 1050 mA 1400 mA ≤ loset ≤ 2100 mA 2800 mA ≤ loset ≤ 4200 mA 4450 mA ≤ loset ≤ 6700 mA
Range	EUG-240S105DT EUG-240S210DT EUG-240S420DT EUG-240S670DT	70 mA 140 mA 280 mA 445 mA	-	loset	70 mA ≤ loset < 700 mA 140 mA ≤ loset <1400 mA 280 mA ≤ loset <2800 mA 445 mA ≤ loset <4450 mA
Recomme Range for	nded Dimming 0-5V	0 V	-	5 V	Dimming mode set to 0-5V in PC interface.
Recomme Range for	nded Dimming 0-10V	0 V	-	10 V	Default 0-10V dimming mode with positive logic.
PWM_in F	PWM_in High Level		-	10 V	
PWM_in Low Level		-0.3 V	-	0.6 V	Dimming mode set to PWM in PC
PWM_in Frequency Range		200 Hz	-	2 KHz	interface.
PWM_in E	Outy Cycle	1%	-	99%	

Note: All specifications are typical at 25°C unless otherwise stated.

Safety &EMC Compliance

Safety Category	Standard
UL/CUL	UL8750,CAN/CSA-C22.2 No. 250.13
CE	EN 61347-1, EN61347-2-13
KS	KS C 7655
EMI Standards	Notes
EMI Standards EN 55015 ⁽¹⁾	Notes Conducted emission Test &Radiated emission Test

5/15

Fax: 86-571-86601139

Rev. E


Safety &EMC Compliance (Continued)

EMI Standards	Notes
	ANSI C63.4 Class B
FCC Part 15 ⁽¹⁾	This device complies with Part 15 of the FCC Rules. Operation is subject to the following two conditions: [1] this device may not cause harmful interference, and [2] this device must accept any interference received, including interference that may cause undesired Operation.
EMS Standards	Notes
EN 61000-4-2	Electrostatic Discharge (ESD): 8 kV air discharge, 4 kV contact discharge
EN 61000-4-3	Radio-Frequency Electromagnetic Field Susceptibility Test-RS
EN 61000-4-4	Electrical Fast Transient / Burst-EFT
EN 61000-4-5	Surge Immunity Test: AC Power Line: line to line 6 kV, line to earth 10 kV (2)
EN 61000-4-6	Conducted Radio Frequency Disturbances Test-CS
EN 61000-4-8	Power Frequency Magnetic Field Test
EN 61000-4-11	Voltage Dips
EN 61547	Electromagnetic Immunity Requirements Applies To Lighting Equipment

Note: (1) This LED driver meets the EMI specifications above, but EMI performance of a luminaire that contains it depends also on the other devices connected to the driver and on the fixture itself.

(2) To perform electric strength (hi-pot) testing, the "GDT ground disconnect" (nut and metal lock sheet) on the driver end-cap should be removed temporarily to prevent the internal gas discharge tube from conducting (as allowed by IEC 60598-1 Clause 10.2). After testing is completed, these items must be reinstalled to restore line-to-earth surge protection and secure the end cap.


Derating




Rev. E

EUG-240SxxxDT


Lifetime vs. Case Temperature



Inrush Current Waveform




Efficiency vs. Load



7/15

Fax: 86-571-86601139


Rev. E




Rev. E

EUG-240SxxxDT

Power Factor



Total Harmonic Distortion



Protection Functions

Parameter	Notes
Over Temperature Protection	Decreases output current, returning to normal after over temperature is removed.
Short Circuit Protection	Auto Recovery. No damage will occur when any output is short circuited. The output shall return to normal when the fault condition is removed.
Over Voltage Protection	Limits output voltage at no load and in case the normal voltage limit fails.


INVENTR®NICS




Dimming

• 0-5V Dimming

The recommended implementation of the dimming control is provided below.



Implementation 1: Positive logic



Implementation 2: Negative logic

Notes:


- 1. The dimmer can also be replaced by an active 0-5V voltage source signal or passive components like resistors and zener.
- 2. Do NOT connect Dim- to the output V- or V+, otherwise the driver will not work properly.
- 3. If 0-5V dimming is not used, Dim + should be open.
- 4. When 0-5V negative logic dimming mode and Dim+ is open, the driver will output maximum current.

• 0-10V Dimming

The recommended implementation of the dimming control is provided below.

Dimming Voltage (V)


INVENTR®NICS



Implementation 3: Positive logic

Dimmer

0%




Implementation 4: Negative logic

Notes:

- 1. The dimmer can also be replaced by an active 0-10V voltage source signal or passive components like resistors and zener.
- 2. Do NOT connect Dim- to the output V- or V+, otherwise the driver will not work properly.
- 3. If 0-10V dimming is not used, Dim + should be open.
- 4. When 0-10V negative logic dimming mode and Dim+ is open, the driver will output minimum current.

PWM Dimming

The recommended implementation of the dimming control is provided below.




Implementation 5: Positive logic

11/15

Fax: 86-571-86601139

Rev. E




Implementation 6: Negative logic

Notes:

- 1. Do NOT connect Dim- to the output V- or V+, otherwise the driver will not work properly.
- 2. If PWM dimming is not used, Dim + should be open.
- 3. When PWM negative logic dimming mode and Dim+ is open, the driver will output minimum current.


Time Dimming



Set the timing curve by pulling the sliders.

Rev. E

Programming Connection Diagram




Note: The driver does not need to be powered on during the programming process.

Please refer to <u>PRG-MUL2</u> (Programmer) datasheet for details


Mechanical Outline

EUG-240S105DT



Rev. E

Others



RoHS Compliance

Our products comply with the European Directive 2011/65/EC, calling for the elimination of lead and other hazardous substances from electronic products.



Rev. E

Revision History

Change		Description of Change					
Date	Rev.	Item	From	То			
2016-02-29	Α	Datasheets Release	/	/			
		Feature	/	Updated			
		General Specifications	Operating Case Temperature for Type TL Tc_TL	Added			
2016-04-08	В	General Specifications	With mounting ear	Updated			
		Safety &EMC Compliance	/	Updated			
		Mechanical Outline	1	Updated			
		Feature	/	Updated			
		Models	1	Updated			
2017-07-04	С	Temperature Coefficient of loset	/	Updated			
2017-07-04		Dimensions	1	Updated			
		Safety &EMC Compliance	1	Updated			
		Mechanical Outline	/	Updated			
00.47 40.00		Features	7 Years Warranty	Added			
2017-10-26	D	Operating Case Temperature for Warranty Tc_w	/	Updated			
		Description	/	Updated			
0040 04 04	_	General Specifications	Lifetime	Updated			
2018-01-31	Е	General Specifications	Operating Case Temperature for Warranty Tc_w	Updated			
		Lifetime vs. Case Temperature	/	Updated			