



JC/JCD Low/Line Voltage

1.6W, 3W

Ideal for use in applications where a halogen G4 12-Volt capsule and G9 120-Volt are used. Illuminate your walkway or accent your landscaping with our naturalLED® Low/Line Voltage Bi-Pin. Our Bi-Pin series produces white light and can replace your current 20 watt halogen G4/G9 capsule.

Rated for 25,000 life hours and should be used in 12 Volt and 120 Volt fixtures only.



Key Features & Benefits

- ▶ Direct replacement and Instant On
- ▶ Up to 84% energy savings
- ▶ Contains no mercury or lead
- ▶ Voltage: 12V/120V
- ▶ Rated 25,000 hours average life
- ▶ 3 Years Limited Warranty

Applications

- ▶ Display Case Lighting
- ▶ Track Lighting
- ▶ Accent Lighting
- ▶ General Lighting
- ▶ Pendant lighting
- ▶ Desk light

Color Choices




Qualifications



ORDERING INFORMATION

Item Code	Description	Color Temp	Wattage	Lumen Output	Equivalent Wattage	Voltage	CRI	Base	Dimmable
5828	LHO-JC1.6T4G4/30K	3000K	1.6	140	20	12V	>80	G4	
5848	LHO-JC1.6T4G4/50K	5000K	1.6	160	20	12V	>80	G4	
5826	LHO-JCD3T4G9/30K	3000K	3	240	30	120V	>80	G9	•
5830	LHO-JCD3T4G9/50K	5000K	3	250	30	120V	>80	G9	•

► Dimensions

 <p>JCD-G9</p> <p>JC-G4</p>	<table border="1"> <thead> <tr> <th>Item</th> <th>A</th> <th>B</th> <th></th> <th>Weight (lbs)</th> </tr> </thead> <tbody> <tr> <td>JC-G4</td> <td>0.55-in</td> <td>1.60-in</td> <td>--</td> <td>0.02</td> </tr> <tr> <td>JCD-G9</td> <td>0.70-in</td> <td>1.80-in</td> <td>--</td> <td>0.04</td> </tr> <tr> <td></td> <td></td> <td></td> <td></td> <td></td> </tr> </tbody> </table>	Item	A	B		Weight (lbs)	JC-G4	0.55-in	1.60-in	--	0.02	JCD-G9	0.70-in	1.80-in	--	0.04									
Item	A	B		Weight (lbs)																					
JC-G4	0.55-in	1.60-in	--	0.02																					
JCD-G9	0.70-in	1.80-in	--	0.04																					

► Master Carton Package

