



100W LED Retrofit Lamp

Order Code: LP28509



DLC Model# OR100-40E39

Description

Venture Lighting's LED Retrofit lamps are the ideal upgrade solution to traditional HID lamp technologies. Venture's LED Retrofit lamps are a simple energy saving solution for providing significant maintenance savings. The integrated driver design is an ideal upgrade from traditional technologies.

Features & Benefits

- Energy saving replacement for MH or HPS
- Up to 5 times longer life and 80% energy savings compared to HID
- 5 year warranty
- Universal burn position
- Easy installation
- Reduced maintenance costs

**Note: It is the customer's responsibility to verify that the lamp compartment meets the minimum required lamp compartment dimension of 5.79" diameter by 16" long.*

Applications

- Post top
- Wall pack
- Area Lighting
- Flood lighting
- Garage lighting
- General illumination

Notes

- The use of an external surge protection device is recommended
- Operating temperature range between -40°F and 122°F (-40°C and 50°C)
- Suitable for use in dry and damp environments
- Suitable for use in portable luminaires, surface mounted and ceiling luminaires
- Suitable for use in totally enclosed, recessed luminaires.
- Do not use where exposed to water or outdoors without an appropriate enclosed luminaire.

Product Performance	
Input Power (W)	100
Bare Lamp Lumens	11000
DLC Rated Lumens	7678
Lumens/Watt (Bare Lamp)	110
Beam Angle (°)	360
Correlated Color Temperature (CCT)	4000K
Color Rendering Index (CRI)	80
Life Hours (L70)	50000
Operating Temperature Range	-30°C to 50°C

Physical Characteristics	
Base Type	Mogul (E39)
Overall Length A	11.42" (290mm)
Diameter B	4.91" (125mm)
Weight	2.6 lbs

Electrical Characteristics	
Input Voltage Range	120V-277V; 50/60Hz
Driver	Internal within lamp
Power Factor	>0.90
THD	<20%

Regulatory Qualifications	
cULus Listed	
DLC Qualified - Model# OR100-40E39	

Accessories	
BSP3-277-LC Surge Protector	



Venture 100W LED Retrofit Lamp

