

# 34 In. 18W (21W Replacement) Selectable White G5 Base Direct Replacement (Type A) (T5 Replacement) LED Linear Tube

## Features

- Works with most electronic ballasts, No rewiring is required
- Shatter-resistant and mercury-free, No special disposal is required
- Flicker-free, instant ON illumination at full brightness
- **Ideal usage:** Office, Garage or Warehouse Lighting



## Specifications

<b>Item Number</b>	<b>Item Length (In)</b>	<b>Item Width (In)</b>	<b>Bulb Shape</b>
T534/4CCT/LED	34.2	0.7	T5
<b>Bulb Type</b>	<b>Bulb Base</b>	<b>Tube Type</b>	<b>Brightness (LUMENS)</b>
Tubular	G5	Type A	1800
<b>Lumen Efficiency (LPW)</b>	<b>Color Accuracy (CRI)</b>	<b>Color Temperature (CCT)</b>	<b>Life Hours</b>
100.0	80	3000 4000 5000 6500	50000
<b>Life Years</b>	<b>Voltage</b>	<b>Replacement</b>	<b>Annual Energy Cost</b>
45.7	120-277	21	2.17
<b>Energy Used (Wattage)</b>	<b>Battery Operated</b>	<b>Pack Quantity</b>	<b>Smart</b>
18	No	1	No
<b>Portable</b>	<b>Dimmable</b>	<b>Hardwire</b>	<b>Enclosed Fixture Rated</b>
No	No	No	Yes
<b>Safety Location</b>	<b>CEC Compliant</b>		
Damp	Not Regulated		