

# 6 In. 15W (32W Replacement) Selectable White G13 Base (T8 Or T8 And T12 Replacement) U-Bend Linear LED Tube

## Features

- Two installation options: plug and play direct replacement or ballast bypass
- Shatter-resistant and mercury-free, no special disposal is required
- Flicker-free, instant ON illumination at full brightness
- **Ideal usage:** General purpose lighting, Task Lighting



## Specifications

<b>Item Number</b>	<b>Item Length (In)</b>	<b>Item Width (In)</b>	<b>Bulb Shape</b>
T848/3CCT/U6/LED	22.7	6.9	T8
<b>Bulb Type</b>	<b>Bulb Base</b>	<b>Bulb Finish</b>	<b>Tube Type</b>
Tubular	G13	White	Type A/B
<b>Technology</b>	<b>Brightness (LUMENS)</b>	<b>Lumen Efficiency (LPW)</b>	<b>Color Accuracy (CRI)</b>
LED - SMD	2100	140.0	80
<b>Color Temperature (CCT)</b>	<b>Life Hours</b>	<b>Life Years</b>	<b>Voltage</b>
3000 4000 6500	50000	45.7	120-277
<b>Replacement</b>	<b>Annual Energy Cost</b>	<b>Energy Efficiency</b>	<b>Energy Used (Wattage)</b>
32	1.81	53.1%	15
<b>Battery Operated</b>	<b>Pack Quantity</b>	<b>Smart</b>	<b>Portable</b>
No	1	No	No
<b>Dimmable</b>	<b>Hardwire</b>	<b>Enclosed Fixture Rated</b>	<b>Safety Location</b>
No	No	No	Damp
<b>Energy Star</b>	<b>CEC Compliant</b>		
No	Not Regulated		